

10
CLAIMS

1. A sparse array antenna comprising series-fed antenna array columns tuned to a respective transmit and receive frequency, **characterised in** that

transmitting and receiving array columns are formed with a given
5 distance between each transmitting radiator element and each receiving radiator element, the series-fed antenna columns being arranged in parallel to each other, thereby forming a symmetric interleaved transmit/receive array;

receiving array columns operate as parasitic elements in a transmit
10 mode and transmitting array columns operate as parasitic elements in a receive mode, thereby reducing creation of grating lobes.

2. The antenna according to claim 1, **characterised in** that

a distance between each transmitting antenna array column and
15 each receiving antenna array column is typically increased to be of an order of one wavelength (λ) to thereby obtain a sparse array.

3. The antenna according to claim 2, **characterised in** that

the series-fed array columns are formed as extended ridged slotted
20 wave-guides tuned to a respective transmitting and receiving frequency.

4. The antenna according to claim 3, **characterised in** that

when having number n of slots in each slotted transmitting wave-
guide the number of slots in each slotted receiving wave-guide being
25 generally $n \pm x$, where x represents an integer digit ($x = 0, 1, 2, 3 \dots$).

5. The antenna according to claim 2, **characterised in** that

the series-fed array columns are formed as extended transmission
lines containing radiation elements, the array columns being tuned to a
30 respective transmitting and receiving frequency.

6. The antenna according to claim 1, **characterised in** that the sparse array antenna is arranged to be scanable to also provide reduced sidelobes entering visual space when scanning the main radiation lobe from an off boresight direction.

5

7. The antenna according to claim 1, **characterised in** that that each one of the series-fed antenna column is narrowly tuned within a respective frequency band to thereby reduce coupling between the transmitting and receiving bands used.

10

8. The antenna according to anyone of the preceding claims, **characterised in** that the series-fed antenna array columns are connected to and fed from an active receive/transmit (T/R) module.

15

9. The antenna according to claim 2, **characterised in** that only one set of series-fed columns being actively used and another interleaved set of series-fed columns are terminated by a suitable load forming parasitic columns of the sparse array antenna.